



## MDL-3160 Smart Drawer Lock User Manual

**Lock :** The handle groove is turned in the red dot direction, which is the locked position.

**Power on :** Tap the sensor once and red light ■ will flash, then you will hear a beep. After leaving, the light turns into blue.

**Unlock :** Press the sensor once until the light ■ turns into green and beeps. Afterwards, turn the handle groove to 3:00 direction and register or clear.



**Register Mode :** The manager is the first register, and only the manager has the authority to clear.

### Manager Registration :

Go to the unlocking place and wait for the light ■ turns into blue. After turning into blue, press the fingerprint sensor until hearing beep. → leave the sensor and the light ■ flashes blue and purple. → Press the sensor again ( Start to register ) →the purple light ■ beeps →turns into blue ■ →Repeat the action three times ( You will hear a beep after every successful sensing ) →Green light ■ lasts after successful scanning. →Long beep ( Successful registration ) →Turns into blue light ■

### User Registration :

Go to the unlocking place and wait for the light ■ turns into blue. After turning into blue, the manager should press the fingerprint sensor until light flashes green ■ and turns into purple ■. → Leave the sensor and the light ■ flashes red and blue. →The user could register and the light turns into green ■ upon successful registration. It will then turns into blue ■ after a long beep.

### Clean-up Mode :



Go to the unlocking place and wait for the light turns into blue■.  
After turning into blue■, the manager should press the fingerprint sensor until light turning into purple■ and beep.(do not leave the sensor)→ Press until the sensor light■ turns into white →Leave the sensor. →As the light■ flashes blue and green, press the sensor twice and you will hear two beeps. → Afterwards, the manager should press the sensor until the light■ flashes green, red, and blue.  
( About 5 seconds) →The light■ will last white after successful registration and beep, followed by flashing green light■ three times.

## Notice :

- Low power : Red LED light flashes three times at the same time and beeps three times.
  - Charging : Red LED light lasts.
  - Full charged : Red LED light turns off.
- When the operation fails, wait for every light to turn off and press the sensor again. Restart the power to operate.

## Contact

**Midas Touch, Inc.**

Tel : +886-2-8953-0862

Fax : +886-2-2952-8441

Email : [contact@midastouchinc.com](mailto:contact@midastouchinc.com)

Website : [www.midastouchinc.com](http://www.midastouchinc.com)

Address : 17F-16, No.1, Sec.1, Zhongshan Rd,  
Banqiao Dist, New Taipei City 22063, Taiwan