



MZD-2200

Z-Wave Wall-mount PIR Motion Sensor



KEY FEATURES

- Z-Wave module inside
- ceiling and wall mount mechanism
- Photoelectric sensor is particularly effective in detecting smoldering fires
- Built-in 85dB sounder and flashing red LED indicate presence of smoke
- Tamperproof protection
- Low-power consumption for long battery life
- Manual test button allows you to easily ensure functioning properly
- Mute mode allows you to silence the detector when there is a false alarm
- Battery capacity detection (with the MZG-2088 Control Gateway)
- Immediately send alert notifications to smart device (with the Cloud Home App)

Home Automation and Smart Home Control

The MZD (Z-Wave Sensing Device) series of Home Automation product family, based on Z-Wave technology, provides the advanced security system that protects your home and family 24/7. Easy operation and flexible configuration are the attractive features of our system; the simple one-touch button lets you program your regular settings according to your preference and operation mode. Worked with MZG-2088 Home Automation Control Gateway, you get the all-round and reliable home security services that we offer. Our full range of product lines ensure that you get all the devices you need for your home security system.

Specifications

Product	MZD-2200A	MZD-2200E
Feature Specification		
Z-Wave Frequency	America: 908.42MHz	Europe: 868.42MHz
Sensor	Photoelectric	
Buzzing Sound Level	85dB, 3m distance	
LED Indicators	Red: Standby mode, low battery warning Yellow: Tamper switch alert, low battery warning, error detection	
Operating Range	Up to 30 meters in open space	
Installation	Wall mount, 4 to 6 inches from the ceiling suggested Ceiling mount Indoor use only	
General		
Power Requirements	CR123A 3V	
Operating Temperature	0 ~ 49 degrees C	
Operating Humidity	10 ~ 95% (non-condensing)	
Weight	144g	
Dimensions (Φ x L)	120 x 48.7 mm	
Emission	CE, FCC	

Ordering Information

MZD-2200A	Z-Wave Ceiling-mount Smoke Detector (FCC-908.42MHz)
MZD-2200E	Z-Wave Ceiling-mount Smoke Detector (ETSI-868.42MHz)